


CTI CIRCUIT DEVICES

MCBs, RCBO & RCDs + MAINS SWITCH

A full range of circuit protection devices to complement the CTI range of consumer units. Includes new type A, DC sensitive RCDs and RCBOs.

Features:

- Double pole mains switch
- B Curve MCBs with 6KA breaking capacity
- Type AC RCDs and RCBOs
- Type A, DC sensitive RCDs and RCBOs
- Designed for use with CTI consumer units



ZMA1



ZR63



ZCBO16/M



ZSPD



ZB06

Specification


Material:	Nylon PA66
Colour Finish:	White
Working Temperature:	Type A RCD's + Type AC RCBO's -5°C to 50°C
IP Rating:	IP20
Guarantee:	5 Years

Dimensions

Mains Switch & RCDs	H: 83 x W: 35 x D: 73mm / Type A RCD's - H: 82 x W: 36 x D: 74mm
MCBs, RCBOs & SPD	H: 83 x W: 17.5 x D: 73mm / Type AC RCBO's - H: 86 x W: 18 x D: 74mm
Surge Protection Device	H: 90 x W: 18 x D: 67mm
Bell Transformer	H: 80 x W: 35 x D: 14mm

Product Code	Description	Rated Current	Weight (Kg)	Barcode
ZMA1	Main Switch - DP	100A	0.18	5055807612326
ZSPD	Surge Protection Device	20kA nom 40kA max	0.16	5055807624329
ZR25	RCD - 30mA Type AC	25A	0.18	5055807612333
ZR40	RCD - 30mA Type AC	40A	0.18	5055807612340
ZR63	RCD - 30mA Type AC	63A	0.18	5055807612364
ZR80	RCD - 30mA Type AC	80A	0.18	5055807612388
ZR80-1	RCD - 100mA Type AC	80A	0.18	5055807612395
ZR25/A	RCD - 30mA Type A	25A	0.23	5055807624220
ZR40/A	RCD - 30mA Type A	40A	0.23	5055807624237
ZR63/A	RCD - 30mA Type A	63A	0.23	5055807624244
ZR80/A	RCD - 30mA Type A	80A	0.23	5055807624251
ZR100/A	RCD - 30mA Type A	100A	0.23	5055807624336
ZB06	MCB - B Curve 6kA	6A	0.1	5055807611992
ZB10	MCB - B Curve 6kA	10A	0.1	5055807612012
ZB16	MCB - B Curve 6kA	16A	0.09	5055807612036
ZB20	MCB - B Curve 6kA	20A	0.09	5055807612050

Product Code	Description	Rated Current	Weight (Kg)	Barcode
ZB32	MCB - B Curve 6kA	32A	0.09	5055807612067
ZB40	MCB - B Curve 6kA	40A	0.09	5055807612074
ZB45	MCB - B Curve 6kA	45A	0.09	5055807612081
ZB50	MCB - B Curve 6kA	50A	0.09	5055807612098
ZB63	MCB - B Curve 6kA	63A	0.09	5055807612104
ZCBO6/M	RCBO - 30mA Type AC	6A	0.14	5055807621915
ZCBO10/M	RCBO - 30mA Type AC	10A	0.14	5055807621922
ZCBO16/M	RCBO - 30mA Type AC	16A	0.14	5055807621939
ZCBO20/M	RCBO - 30mA Type AC	20A	0.14	5055807621946
ZCBO32/M	RCBO - 30mA Type AC	32A	0.14	5055807621953
ZCBO40/M	RCBO - 30mA Type AC	40A	0.14	5055807621960
ZCBO6/M/A	RCBO - 30mA Type A	6A	0.16	5055807624268
ZCBO10/M/A	RCBO - 30mA Type A	10A	0.16	5055807624275
ZCBO16/M/A	RCBO - 30mA Type A	16A	0.16	5055807624282
ZCBO20/M/A	RCBO - 30mA Type A	20A	0.16	5055807624299
ZCBO32/M/A	RCBO - 30mA Type A	32A	0.16	5055807624305
ZCBO40/M/A	RCBO - 30mA Type A	40A	0.16	5055807624312
ZBL	Bell Transformer 4P 8VA	8VA	0.16	5055807612111



UK
CA



CE